THE T A E R F SCIENTIFIC RAILGUN THEORETICAL PERFORMANCE

Richard A. Marshall

Presented at the
Conference on Electromagnetic Guns and Launchers
San Diego, California
November 3-6, 1980

Publication No. PR-10
Center for Electromechanics
The University of Texas at Austin
Balcones Research Center
EME 1.100, Building 133
Austin, TX 78758-4497
(512)471-4496

Abstract

The successful demonstration of direct-current railguns during the last decade has shown that these simple devices have the capability of accelerating gram-sized projectiles to very high velocities, provided that the current and energy is fed into the accelerator in an appropriately controlled manner. Two current-control devices have been used successfully, the large inductor and the explosive flux compressor.

In the experiments done to date, only a single power supply device has been used, connected to the breech end of the rails. The performance of these railguns was limited by such factors as the electrical resistance of the rails, however, and improved performance is expected to be obtained by using many energy stores distributed along the length of the gun.

The Center for Electromechanics at the University of Texas at Austin is funded to build a distributed energy store railgun. The theoretical performance of this gun is examined for several cases in which different numbers of energy stores are used.

Introduction

The desirability of producing very high velocities (>20 km/s) in gram-sized macroparticles is now fairly generally accepted.

Applications are seen in the general field of impact physics, and the specific possibility of nuclear fusion by impact is now accepted.^{1,2}

Such velocities might be achieved in a variety of electromagnetic ways. One of these is the traveling magnetic-wave accelerator, the best-known example of which is the MIT-Princeton mass driver.³ An early writer on this method was Winterberg⁴ and the most recent champion in the area is Chen.⁴ Another related device is the Jaycor plasma squeeze gun.⁶ The railgun was reinvented at the Australian National University^{7,8,9} about ten years ago and used a single large inductor as its power source. More recently the LLNL/LASL group has successfully demonstrated the use of explosively driven flux compression power sources to power a variety of railguns.¹⁰

Another promising railgun system is one that uses energy stores distributed along the gun, and we confine our attention here to this system.

Analysis

In an earlier paper we presented a method by which a distributed energy store railgun might be simulated on a computer.¹¹ It was assumed that each energy store consisted of an inductor charged with some particular current at the moment of switching into the gun. The method is now extended to include the charging of the inductors.

Figure 1 is a schematic representation of a railgun with capacitor-charged inductors distributed along its length. The stores--each consisting of a primary storage capacitor (capacitance C and initial

Fig. 1. Circuit diagram showing parameters and variables used in the analysis

voltage V_n) and a secondary storage inductor (inductance L and resistance R)--are spaced at intervals ℓ along the rails. The projectile, shown having moved a distance x into gun section number 1, has a mass m , velocity $\dot{x}$, and acceleration $\ddot{x}$. The railgun has an inductance and resistance of L' and R' per unit length.

The currents I_n flow as shown. The diode shown across each capacitor indicates a crowbar. The upper diodes indicate that the current is prevented from flowing in the reverse direction when the inductor is discharged. The arc armature has a volt drop of U .

The rates of change of current $\dot{I}_n$ flowing in each energy store can be obtained from equation (1). This expression is the same as that derived in reference 11, except for the inclusion of the V_n terms.

$$\begin{bmatrix} (L+L'x) & L'x & L'x & L'x.. \\ -L & (L+L'\ell) & L'\ell & L'\ell.. \\ 0 & -L & (L+L'\ell) & L'\ell.. \\ 0 & 0 & -L & (L+L'\ell).. \\ \dots & \dots & \dots & \dots \end{bmatrix} \begin{bmatrix} \dot{I}_1 \\ \dot{I}_2 \\ \dot{I}_3 \\ \dot{I}_4 \\ \dots \end{bmatrix} = \begin{bmatrix} R(-I_1) - (L'\dot{x}+R'x)(I_1+I_2+I_3+I_4+)+V_1-U \\ R(I_1-I_2) & -R'\ell(I_2+I_3+I_4+)-V_1+V_2 \\ R(I_2-I_3) & -R'\ell(I_3+I_4+)-V_2+V_3 \\ R(I_3-I_4) & R'\ell(I_4+)-V_3+V_4 \\ \dots & \dots \end{bmatrix} \quad (1)$$

The simulation is performed in the following manner: At the beginning of each computational step, all the terms in (1) are known except $\dot{I}_n$, thus the values of $\dot{I}_n$ can be found, allowing the new values for I_n to be calculated. Projectile acceleration $\dot{x}$ is then found from the expression

$$\dot{x} = L'(\sum I_n)^2/2m \quad (2)$$

from which the new values of $\dot{x}$ and x can be found. The new values of V_n are found from

$$V_n - \frac{I_n}{C} \Delta t \rightarrow V_n. \quad (3)$$

At each step the value of x is tested and when it gets greater than ℓ , it is replaced by $(x-\ell)$ and at the same time all the currents and capacitor voltages are shifted one gun stage. The dimensions of the matrixes are also increased by one because there is now one more power circuit in action. At each step also, the magnitude of the current in the rearmost energy store is checked and when it drops below zero, that store is "removed" by reducing the matrix dimensions by one. The values of V_n are also checked and the capacitors "crowbarred" by holding V_n zero rather than allowing them to swing negative.

The Railgun Simulations

The following four simulations are made using the parameter values for the TAERF railgun.¹² The first two simulations show the performance

of a one- and a two-stage gun.

capacitor voltage	6000 V
capacitance	180 μ F
coil inductance	1.32 μ H
coil resistance	1 m Ω
gun inductance	0.6 μ H/m
gun resistance	2 m Ω /m
projectile mass	1.8 g
armature arc drop	160 V
injection velocity	720 m/s
1st-stage length	7.6 cm (3")
2nd-stage length	11.4 cm (4.5")
(total length	19 cm)

Fig. 2. Simulation of one-stage gun (a) and two-stage gun (b) showing current versus distance along the gun. In (b) the upper curve is total current, the lower curves being the stage currents. Velocity gain in (a) 96 m/s. Velocity gain in (b) 56 m/s in 1st stage, 248 m/s total.

Slightly different parameters are used for the 10- and 20-energy-store simulations shown in figures 3 and 4 to match those of the capacitors that we intend to eventually make use of. The coil inductance has been changed to keep the peak current in each energy store at 70 kA. The projectile mass has been reduced to the polycarbonate-only value; at present a brass washer is screwed to the projectile's rear face to facilitate establishing the first arc.

The parameters are

capacitor voltage	10,000 V	projectile mass	1.3 g
capacitance	160 μF	armature arc drop	160 V
coil inductance	3.27 μH	injection velocity	1000 m/s
coil resistance	1 $\text{m}\Omega$	energy stores at	5/m
gun inductance	0.6 $\mu\text{H/m}$	no. of stores	10 and 20
gun resistance	2 $\text{m}\Omega/\text{m}$

Fig. 3. Simulation of a 10-energy-store railgun

Fig. 4. Simulation of a 20-energy-store railgun

The velocity indicated at the end of the tenth stage of the 10-stage gun is 5.77 km/s; if allowed to travel one further stage, length would reach 6.12 km/s.

At the end of the twentieth stage of the 20-stage gun, velocity is 9.96 km/s; after traveling two further stage lengths, it is 10.48 km/s.

Discussion of Simulations

The most interesting point to note is how small the ripple in the driving current becomes as the number of energy stores is increased. This smoothing out becomes pronounced as the time of energy transfer, capacitor to inductor, becomes significant compared with the transit time of the projectile through the stage, the effect being the greatest

when the two times are equal.

If the ripple is defined as the ratio of ripple amplitude divided by the current, then the ripple continues to decrease as the number of stores delivering current at one time increases. This is a continuing effect. As the projectile's speed increases, the propulsive efficiency continues to increase, so the magnitude of the current increases, thus ripple decreases.

The practical importance of current ripple will be the oscillation in propelling force that it produces. The way in which thrust increases, as an energy store is switched into the gun, is examined in the next section.

Force Pick-up

If the current from an energy store in the distributed energy store railgun is turned on at the instant that the effective current center of the armature is in line with current feed conductor, then it is not correct to say that $F = 0.5L'(\Sigma I)^2$. This is because the expression relating force to the inductance of the gun rails is a kind of convenient fiction. What really happens is that the force arises by the interaction of the armature current with the field produced by the flow of current in the rails. In the case given, the new current produces no useful field because it does flow along the rails. The situation is shown in figure 5.

At the instant before I_n is turned on, the force produced, $F(I_0)$, is given by

$$\begin{aligned} F(I_0) &= 0.5 L' (I_0)^2 \\ &= B(I_0) I_0 w \end{aligned}$$

$$\text{giving } B(I_0) = 0.5 L' I_0 / w \quad (4)$$

where $B(I_0)$ is the effective field produced by the current I_0 .

At the instant I_n is turned on ($x=0$) the force, $F(I_0+I_n, 0)$ is given by

$$F(I_0+I_n, 0) = B(I_0) (I_0+I_n) w$$

Fig. 5. Current switch-in

and when the projectile has moved a distance x from this position

$$F(I_o + I_n, x) = (B(I_o) + B(I_n))(I_o + I_n)w \dots \quad (5)$$

Making the simplifying assumption that each rail consists of a single filament, and using the proportionality constants from equation 4, the form of $B(I_n)$ as a function of x/w (see fig. 5) may be obtained:

$$B(I_n) = \frac{0.5 L' I_n}{w} \cdot \frac{x/w}{\sqrt{1/4 + x^2/w^2}} \quad (6)$$

Substituting (6) and (4) into (5) gives

$$F(I_o + I_n, x) = 0.5 L' (I_o + I_n \frac{x/w}{\sqrt{1/4 + x^2/w^2}}) (I_o + I_n)$$

giving

$$\frac{F(I_0 + I_n, x)}{F(I_0)} = 1 + \frac{I_n}{I_0} \cdot \left(\frac{x/w}{\sqrt{1/4 + x^2/w^2}} \right) \left(1 + \frac{I_n}{I_0} \right). \quad (7)$$

A plot of this relationship is shown in figure 6.

Fig. 6. Ratio of propulsive force as a function of projectile travel for a step increase in gun current

It is seen therefore that the full effect of the current from an energy store is not felt by the projectile until it has traveled about one gun width. This will be a significant effect if energy stores are spaced a few gun widths apart. In this instance, and for a step input, the effect will be to lop the force peak, that is, to "soften the ride".

Skin Effect in the Rails

Finally a simple dimension analysis of rail skin effect is

made because study of the simulations indicates that rail resistance causes a significant part of the system losses.

Fig. 7. Schematic representation of a plasma armature

Figure 7 shows a projectile traveling at velocity V between a pair of rails, driven by a plasma armature of length S . For the sake of this discussion, assume that the current density in the plasma is uniform, then at any position along the rails, the rail sees a ramp current input rising from zero to full current in a time $t = S/V$, the time taken for the armature to travel its own length. The resulting depth d of current penetration in a copper rail is given approximately by

$$d = 0.1 \sqrt{t} = 0.1 \sqrt{S} / \sqrt{V} . \quad (8)$$

Thus, for rails of height h , gun-rail resistance R' is given by

$$R' = \frac{2\rho}{hd} = \frac{20\rho\sqrt{V}}{h\sqrt{S}} \quad (9)$$

Since the "shape" of the current following the projectile tends to remain fixed with respect to space (rather than time), the energy loss in a given rail length will be proportional to R'/V , that is, $1/\sqrt{V}$ (substituting for R' from (9)) showing that as far as rail losses are concerned, efficiency will continue to rise as velocity increases.

As far as the numbers are concerned, if S is taken as 5 cm, the

current will fully penetrate rails 1.5-mm thick when the velocity reaches 225 m/s.

Note that if S should be 20 cm rather than 5 cm, then the value for R' will be halved. The importance of understanding the behavior of plasma armatures can therefore readily be seen. A promising start has been made on this problem.^{13,14}

Conclusion

It has been shown that the performance of real, distributed energy store railgun systems may be readily simulated, and that the concept offers the probability of propelling macroparticles to very high velocities. It is also shown that the effect of skin depth in the rails does not offer an insuperable difficulty. The importance of understanding the nature of the plasma armature is also indicated.

CEM-UT wishes to express its appreciation to the Texas Atomic Energy Research Foundation for support of this research.

References

1. A. T. Peaslee, comp., Proceedings of the Impact Fusion Workshop, Los Alamos Scientific Laboratory Conference no. LA-8000-C, July 1979.
2. F. L. Ribe and A. T. Peaslee, principal investigators, Evaluation of Impact Fusion Concepts, final report to Office of Energy Research, contract no. EY-76-S-06-2225, January 1980.
3. H. Kolm et al., "Electromagnetic Propulsion Alternatives," (Paper read at Princeton Symposium on Space Manufacturing, 1979).
4. F. Winterberg, Z. Naturforsch. 19: 231-39, 1964.
5. K. W. Chen, "A Magnetic Projectile Launcher Concept for Hypervelocity Research," proceedings of this conference.
6. D. A. Tidman and S. A. Goldstein, "Mass Accelerator for Producing Hypervelocity Projectiles Using a Series of Imploding Annular Discharges," in Proceedings of Impact Fusion Workshop, comp. A. T. Peaslee, Los Alamos Scientific Laboratory Conference no. LA-8000-C, July 1979.
7. J. P. Barber, "The Acceleration of Macroparticles and a Hypervelocity Electromagnetic Accelerator," (Ph.D. thesis, Australian National University, 1972).
8. S. C. Rashleigh and R. A. Marshall, "Electromagnetic Acceleration of Macroparticles to High Velocities," J. Appl. Phys. 49(4), April 1978.
9. R. A. Marshall, "The Rail Gun Installation," in "High Power High Energy Pulse Production and Application," ed., E. K. Inall, (Canberra: ANU Press, 1978).
10. R. S. Hawke et al., "Results of Magnetic Flux Compression Generator Powered Rail Gun Experiments," proceedings of this conference.
11. R. A. Marshall and W. F. Weldon, "Analysis of Performance of Rail-Gun Accelerators Powered by Distributed Energy Stores," in Proceedings of the IEEE 1980 Fourteenth Pulse Power Modulator Symposium.
12. Texas Atomic Energy Research Foundation Project Report No. 34, May 1, 1980 to October 31, 1980.

References, continued

13. I. R. McNab, "Electromagnetic Macroparticle Acceleration by High Pressure Plasma," J. Appl. Phys. 51(5), May 1980.
14. J. D. Powell and J. H. Batteh, "Arc Dynamics in the Rail Gun," proceedings of this conference.